

Helgonsken G2

Inställningar drivdon

Helgonsken, 4000K, 40W On-Off								
Driver setting	24.6W	200mA	30.27W	250mA	36.88W	300mA	43.11W	350mA
Luminious flux (lm)	3500		4334		5206		5980	
Helgonsken, 3000K, 40W On-Off								
Driver setting	24,9W	200mA	30,61W	250mA	37,22W	300mA	43,45W	350mA
Luminious flux (lm)	3262		4031		4831		5544	
Helgonsken, 4000K, 40W DALI								
Driver setting	10W	75mA	18,95W	150mA	32W	250mA	44,5W	350mA
Luminious flux (lm)	1338		2648		4460		6047	
Helgonsken, 3000K, 40W DALI								
Driver setting	10W	75mA	19,2W	150mA	32,25W	250mA	44,75W	350mA
Luminious flux (lm)	1251		2467		4134		5607	

On/Off

Output			1	2
Prated(W)	Irated(mA)	Voltage(Vdc)		
26.60	200	50-133	--	--
33.25	250	50-133	--	ON
39.90	300	50-133	ON	--
39.90	350 ★	50-114	ON	ON

DALI

Output			1	2	3	4	Dimming depth
Prated(w)	Irated(mA)	Voltage(Vdc)					
18.0	75	54-240	ON	—	ON	ON	4.0%(3mA)
24.0	100	54-240	—	—	ON	ON	3.0%(3mA)
30.0	125	54-240	ON	ON	—	ON	2.4%(3mA)
36.0	150	54-240	—	ON	—	ON	2.0%(3mA)
39.9	175	54-228	ON	—	—	ON	1.7%(3mA)
40.0	200	54-200	—	—	—	ON	1.5%(3mA)
39.8	225	54-177	ON	ON	ON	—	1.3%(3mA)
40.0	250	54-160	—	ON	ON	—	1.2%(3mA)
39.9	275	54-145	ON	—	ON	—	1.1%(3mA)
39.9	300	54-133	—	—	ON	—	1.0%(3mA)
40.0	325	54-123	ON	ON	—	—	0.9%(3mA)
39.9	350	54-114	—	ON	—	—	0.9%(3mA)
39.8	375	54-106	ON	—	—	—	0.8%(3mA)
40.0	400 ★	54-100	—	—	—	—	0.8%(3mA)

★ = fabriksinställning